



NMEA Reference Manual

SiRF Technology, Inc.
217 Devcon Drive
San Jose, CA 95112 U.S.A.
Phone: +1 (408) 467-0410
Fax: +1 (408) 467-0420
www.SiRF.com

Part Number: 1050-0042
Revision 1.7, August 2006

SiRF, SiRFstar, and SiRF plus orbit design are registered in the U.S. Patent and Trademark Office. This document contains information on a product under development at SiRF. The information is intended to help you evaluate this product. SiRF reserves the right to change or discontinue work on this product without notice.

NMEA Reference Manual

Copyright © 1996-2006 SiRF Technology, Inc. All rights reserved.

No part of this work may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or by any information storage or retrieval system without the prior written permission of SiRF Technology, Inc. unless such copying is expressly permitted by United States copyright law. Address inquiries to Legal Department, SiRF Technology, Inc., 217 Devcon Drive, San Jose, California 95112, United States of America.

About This Document

This document contains information on SiRF products. SiRF Technology, Inc. reserves the right to make changes in its products, specifications and other information at any time without notice. SiRF assumes no liability or responsibility for any claims or damages arising out of the use of this document, or from the use of integrated circuits based on this document, including, but not limited to claims or damages based on infringement of patents, copyrights or other intellectual property rights. SiRF makes no warranties, either express or implied with respect to the information and specifications contained in this document. Performance characteristics listed in this data sheet do not constitute a warranty or guarantee of product performance. All terms and conditions of sale are governed by the SiRF Terms and Conditions of Sale, a copy of which you may obtain from your authorized SiRF sales representative.

Getting Help

If you have any problems contact your SiRF representative or call or send an e-mail to the SiRF Technology support group:

phone +1 (408) 467-0410

e-mail support@sirf.com

Contents

Preface	vii
1. Output Messages.....	1-1
GGA —Global Positioning System Fixed Data	1-2
GLL—Geographic Position - Latitude/Longitude	1-4
GSA—GNSS DOP and Active Satellites	1-4
GSV—GNSS Satellites in View.....	1-5
MSS—MSK Receiver Signal.....	1-5
RMC—Recommended Minimum Specific GNSS Data	1-6
VTG—Course Over Ground and Ground Speed	1-7
ZDA—SiRF Timing Message	1-7
150—OkToSend.....	1-8
151—GPS Data and Extended Ephemeris Mask	1-8
152—Extended Ephemeris Integrity	1-9
154—Extended Ephemeris ACK	1-9
Reserved - Message ID 225	1-10
2. Input Messages	2-1
Transport Message	2-1
NMEA Input Messages	2-2
100—SetSerialPort.....	2-3
101—NavigationInitialization	2-3
102—SetDGPSPort	2-4
103—Query/Rate Control	2-5

104—LLANavigationInitialization	2-6
105—Development Data On/Off	2-7
106—Select Datum	2-7
107—Extended Ephemeris Proprietary 1	2-8
108—Extended Ephemeris Proprietary 2	2-8
110—Extended Ephemeris Debug	2-9
200—Marketing Software Configuration	2-9
MSK—MSK Receiver Interface	2-11

Tables

Table 1-1	NMEA Output Messages	1-1
Table 1-2	Supported NMEA Output Messages	1-2
Table 1-3	GGA Data Format	1-3
Table 1-4	Position Fix Indicator	1-3
Table 1-5	GLL Data Format	1-4
Table 1-6	GSA Data Format	1-4
Table 1-7	Mode 1	1-5
Table 1-8	Mode 2	1-5
Table 1-9	GSV Data Format	1-5
Table 1-10	MSS Data Format	1-6
Table 1-11	RMC Data Format	1-6
Table 1-12	VTG Data Format	1-7
Table 1-13	ZDA Data Format	1-7
Table 1-14	OkToSend Message Data Format	1-8
Table 1-15	GPS Data and Ephemeris Mask - Message 151	1-8
Table 1-16	Extended Ephemeris Integrity - Message 152	1-9
Table 1-17	Extended Ephemeris ACK - Message 154	1-10
Table 2-1	Transport Message Parameters	2-1
Table 2-2	NMEA Input Messages	2-2
Table 2-3	Supported NMEA Input Messages	2-2
Table 2-4	Set Serial Port Data Format	2-3
Table 2-5	Navigation Initialization Data Format	2-3
Table 2-6	Reset Configuration - Non SiRFLoc Platforms	2-4

Table 2-7	Reset Configuration - SiRFLoc Specific	2-4
Table 2-8	Set DGPS Port Data Format	2-5
Table 2-9	Query/Rate Control Data Format (See example 1)	2-5
Table 2-10	Messages	2-6
Table 2-11	LLA Navigation Initialization Data Format	2-6
Table 2-12	Reset Configuration	2-7
Table 2-13	Development Data On/Off Data Format	2-7
Table 2-14	Select Datum Data Format	2-8
Table 2-15	Extended Ephemeris Proprietary 1	2-8
Table 2-16	Extended Ephemeris Proprietary 2	2-8
Table 2-17	Extended Ephemeris Debug	2-9
Table 2-18	GSC2xr Marketing Software Configuration	2-10
Table 2-19	GSC2xr Marketing Software Configurations	2-10
Table 2-20	RMC Data Format	2-11

Preface



All SiRF products support a subset of the NMEA-0183 standard for interfacing marine electronic devices as defined by the National Marine Electronics Association (NMEA).

The *NMEA Reference Manual* provides details of NMEA messages developed and defined by SiRF. It does not provide information about the complete NMEA-0183 interface standard.

Who Should Use This Guide

This manual was written assuming the user has a basic understanding of interface protocols and their use.

How This Guide Is Organized

This manual contains the following chapters:

Chapter 1, “Output Messages” defines SiRF developed NMEA output messages.

Chapter 2, “Input Messages” defines SiRF developed NMEA input messages.

Related Manuals

You can refer to the following document for more information:

- *NMEA-0183 Standard For Interfacing Marine Electronic Devices*
- *SiRF Binary Protocol Reference Manual*
- *SiRF Evaluation Kit User Guide*
- *SiRF System Development Kit User Guide*



Contacting SiRF Technical Support

Address:

SiRF Technology Inc.
217 Devcon Drive
San Jose, CA 95112 U.S.A.

SiRF Technical Support:

Phone: +1 (408) 467-0410 (9 am to 5 pm Pacific Standard Time)
E-mail: support@sirf.com

General enquiries:

Phone: +1 (408) 467-0410 (9 am to 5 pm Pacific Standard Time)
E-mail: gps@sirf.com

Output Messages



Table 1-1 lists each of the NMEA output messages specifically developed and defined by SiRF for use within SiRF products.

Table 1-1 NMEA Output Messages

Option	Description
GGA	Time, position and fix type data.
GLL	Latitude, longitude, UTC time of position fix and status.
GSA	GPS receiver operating mode, satellites used in the position solution, and DOP values.
GSV	The number of GPS satellites in view satellite ID numbers, elevation, azimuth, and SNR values.
MSS	Signal-to-noise ratio, signal strength, frequency, and bit rate from a radio-beacon receiver.
RMC	Time, date, position, course and speed data.
VTG	Course and speed information relative to the ground.
ZDA	PPS timing message (synchronized to PPS).
150	OK to send message.
151	GPS Data and Extended Ephemeris Mask
152	Extended Ephemeris Integrity
154	Extended Ephemeris ACK

A full description of the listed NMEA messages are provided in the following sections.

Table 1-2 provides a summary of SiRF NMEA output messages supported by the specific SiRF platforms.

Table 1-2 Supported NMEA Output Messages

Message	SiRF Software Options				
	GSW2 ¹	SiRFDRIve ¹	SiRFXTrac ¹	SiRFLoc ¹	GSW3 GSW3LT ¹
GGA	Yes	Yes	Yes	Yes	Yes
GLL	Yes	Yes	Yes	Yes	Yes
GSA	Yes	Yes	Yes	Yes	Yes
GSV	Yes	Yes	Yes	Yes	Yes
MSS	Yes	No	No	No	Yes ²
RMC	Yes	Yes	Yes	Yes	Yes
VTG	Yes	Yes	Yes	Yes	Yes
ZDA	2.3.2 and above	No	No	No	No
150	2.3.2 and above	No	No	No	No
151	2.5 and above	No	2.3 and above	No	3.2.0 and above
152	2.5 and above	No	2.3 and above	No	3.2.0 and above
154	2.5 and above	No	2.3 and above	No	3.2.0 and above

1. GSW2 and SiRFDRIve software only output NMEA version 2.20 (and earlier). SiRFXTrac, GSW3, and GSW3LT software have conditional defines (UI_NMEA_VERSION_XXX) to allow a choice between NMEA 2.20 and 3.00. The file NMEA_SIF.H contains the NMEA version defines.

2. MSS message for GSW3 and GSW3LT is empty since they do not support BEACON.

GGA—Global Positioning System Fixed Data

Note – Fields marked in italic *red* apply only to NMEA version 2.3 (and later) in this NMEA message description.

Table 1-3 contains the values for the following example:

\$GPGGA,161229.487,3723.2475,N,12158.3416,W,1,07,1.0,9.0,M,,0000*18

Table 1-3 GGA Data Format

Name	Example	Units	Description
Message ID	\$GPGGA		GGA protocol header
UTC Time	161229.487		hhmmss.sss
Latitude	3723.2475		ddmm.mmmm
N/S Indicator	N		N=north or S=south
Longitude	12158.3416		dddmm.mmmm
E/W Indicator	W		E=east or W=west
Position Fix Indicator	1		See Table 1-4
Satellites Used	07		Range 0 to 12
HDOP	1.0		Horizontal Dilution of Precision
MSL Altitude	9.0	meters	
Units	M	meters	
Geoid Separation		meters	
Units	M	meters	
Age of Diff. Corr.		second	Null fields when DGPS is not used
Diff. Ref. Station ID	0000		
Checksum	*18		
<CR> <LF>			End of message termination

Table 1-4 Position Fix Indicator

Value	Description
0	Fix not available or invalid
1	GPS SPS Mode, fix valid
2	Differential GPS, SPS Mode, fix valid
3-5	Not supported
6	<i>Dead Reckoning Mode, fix valid</i>

Note – A valid position fix indicator is derived from the SiRF Binary M.I.D. 2 position mode 1. See the *SiRF Binary Protocol Reference Manual*.

GLL—Geographic Position - Latitude/Longitude

Note – Fields marked in italic *red* apply only to NMEA version 2.3 (and later) in this NMEA message description.

Table 1-5 contains the values for the following example:

\$GPGLL,3723.2475,N,12158.3416,W,161229.487,A,A*41

Table 1-5 GLL Data Format

Name	Example	Units	Description
Message ID	\$GPGLL		GLL protocol header
Latitude	3723.2475		ddmm.mmmm
N/S Indicator	N		N=north or S=south
Longitude	12158.3416		dddmm.mmmm
E/W Indicator	W		E=east or W=west
UTC Time	161229.487		hhmmss.sss
Status	A		A=data valid or V=data not valid
<i>Mode</i>	<i>A</i>		<i>A=Autonomous, D=DGPS, E=DR (Only present in NMEA version 3.00)</i>
Checksum	*41		
<CR> <LF>			End of message termination

GSA—GNSS DOP and Active Satellites

Note – Fields marked in italic *red* apply only to NMEA version 2.3 (and later) in this NMEA message description.

Table 1-6 contains the values for the following example:

\$GPGSA,A,3,07,02,26,27,09,04,15,, , , , ,1.8,1.0,1.5*33

Table 1-6 GSA Data Format

Name	Example	Units	Description
Message ID	\$GPGSA		GSA protocol header
Mode 1	A		See Table 1-7
Mode 2	3		See Table 1-8
Satellite Used ¹	07		Sv on Channel 1
Satellite Used ¹	02		Sv on Channel 2
....		
Satellite Used ¹			Sv on Channel 12
PDOP	1.8		Position Dilution of Precision
HDOP	1.0		Horizontal Dilution of Precision
VDOP	1.5		Vertical Dilution of Precision
Checksum	*33		
<CR> <LF>			End of message termination

1. Satellite used in solution.

Table 1-7 Mode 1

Value	Description
M	Manual—forced to operate in 2D or 3D mode
A	2D Automatic—allowed to automatically switch 2D/3D

Table 1-8 Mode 2

Value	Description
1	Fix not available
2	2D (<4 SVs used)
3	3D (>3 SVs used)

GSV—GNSS Satellites in View

Table 1-9 contains the values for the following example:

\$GPGSV,2,1,07,07,79,048,42,02,51,062,43,26,36,256,42,27,27,138,42*71

\$GPGSV,2,2,07,09,23,313,42,04,19,159,41,15,12,041,42*41

Table 1-9 GSV Data Format

Name	Example	Units	Description
Message ID	\$GPGSV		GSV protocol header
Number of Messages ¹	2		Range 1 to 3
Message Number ¹	1		Range 1 to 3
Satellites in View	07		
Satellite ID	07		Channel 1 (Range 1 to 32)
Elevation	79	degrees	Channel 1 (Maximum 90)
Azimuth	048	degrees	Channel 1 (True, Range 0 to 359)
SNR (C/No)	42	dBHz	Range 0 to 99, null when not tracking
....		
Satellite ID	27		Channel 4 (Range 1 to 32)
Elevation	27	degrees	Channel 4 (Maximum 90)
Azimuth	138	degrees	Channel 4 (True, Range 0 to 359)
SNR (C/No)	42	dBHz	Range 0 to 99, null when not tracking
Checksum	*71		
<CR> <LF>			End of message termination

1. Depending on the number of satellites tracked, multiple messages of GSV data may be required.

MSS—MSK Receiver Signal

Note – Fields marked in italic *red* apply only to NMEA version 2.3 (and later) in this NMEA message description.

This message for GSW3 and GSW3LT is empty since they do not support BEACON.

Table 1-10 contains the values for the following example:

\$GPMSS , 55,27,318.0,100,1,*57

Table 1-10 MSS Data Format

Name	Example	Units	Description
Message ID	\$GPMSS		MSS protocol header
Signal Strength	55	dB	SS of tracked frequency
Signal-to-Noise Ratio	27	dB	SNR of tracked frequency
Beacon Frequency	318.0	kHz	Currently tracked frequency
Beacon Bit Rate	100		bits per second
<i>Channel Number</i>	<i>1</i>		<i>The channel of the beacon being used if a multi-channel beacon receiver is used</i>
Checksum	*57		
<CR> <LF>			End of message termination

Note – The MSS NMEA message can only be polled or scheduled using the MSK NMEA input message. See “MSK—MSK Receiver Interface” on page 2-11.

RMC—Recommended Minimum Specific GNSS Data

Note – Fields marked in italic *red* apply only to NMEA version 2.3 (and later) in this NMEA message description.

Table 1-11 contains the values for the following example:

\$GPRMC , 161229.487,A,3723.2475,N,12158.3416,W,0.13,309.62,120598, ,*10

Table 1-11 RMC Data Format

Name	Example	Units	Description
Message ID	\$GPRMC		RMC protocol header
UTC Time	161229.487		hhmmss.sss
Status ¹	A		A=data valid or V=data not valid
Latitude	3723.2475		ddmm.mmmm
N/S Indicator	N		N=north or S=south
Longitude	12158.3416		dddmm.mmmm
E/W Indicator	W		E=east or W=west
Speed Over Ground	0.13	knots	
Course Over Ground	309.62	degrees	True
Date	120598		ddmmyy
Magnetic Variation ²		degrees	E=east or W=west
East/West Indicator ²	E		E=east
<i>Mode</i>	<i>A</i>		<i>A=Autonomous, D=DGPS, E=DR</i>
Checksum	*10		
<CR> <LF>			End of message termination

1. A valid status is derived from the SiRF Binary M.I.D 2 position mode 1. See the *SiRF Binary Protocol Reference Manual*.

2. SiRF Technology Inc. does not support magnetic declination. All “course over ground” data are geodetic WGS84 directions.

VTG—Course Over Ground and Ground Speed

Note – Fields marked in italic *red* apply only to NMEA version 2.3 (and later) in this NMEA message description.

Table 1-12 contains the values for the following example:

\$GPVTG,309.62,T,M,0.13,N,0.2,K,A*23

Table 1-12 VTG Data Format

Name	Example	Units	Description
Message ID	\$GPVTG		VTG protocol header
Course	309.62	degrees	Measured heading
Reference	T		True
Course		degrees	Measured heading
Reference	M		Magnetic ¹
Speed	0.13	knots	Measured horizontal speed
Units	N		Knots
Speed	0.2	km/hr	Measured horizontal speed
Units	K		Kilometers per hour
<i>Mode</i>	<i>A</i>		<i>A=Autonomous, D=DGPS, E=DR</i>
Checksum	*23		
<CR> <LF>			End of message termination

1. SiRF Technology Inc. does not support magnetic declination. All “course over ground” data are geodetic WGS84 directions.

ZDA—SiRF Timing Message

Outputs the time associated with the current 1 PPS pulse. Each message is output within a few hundred ms after the 1 PPS pulse is output and tells the time of the pulse that just occurred.

Table 1-13 contains the values for the following example:

\$GPZDA,181813,14,10,2003,00,00*4F

Table 1-13 ZDA Data Format

Name	Example	Units	Description
Message ID	\$GPZDA		ZDA protocol header
UTC time	181813	hhmmss	The UTC time units are as follow: hh = UTC hours from 00 to 23 mm = UTC minutes from 00 to 59 ss = UTC seconds from 00 to 59 Either using valid IONO/UTC or estimated from default leap seconds
Day	14		01 TO 31
Month	10		01 TO 12
Year	2003		1980 to 2079
Local zone hour	00	hour	Offset from UTC (set to 00)
Local zone minutes	00	minute	Offset from UTC (set to 00)
Checksum	*4F		
<CR> <LF>			End of message termination

150—OkToSend

This message is being sent out during the trickle power mode to communicate with an outside program such as SiRFDemo to indicate whether the receiver is awake or not.

Table 1-14 contains the values for the following examples:

1. OkToSend

\$PSRF150,1*3F

2. not OkToSend

\$PSRF150,0*3E

Table 1-14 OkToSend Message Data Format

Name	Example	Units	Description
Message ID	\$PSRF150		PSRF150 protocol header
OkToSend	1		1=OK to send, 0=not OK to send
Checksum	*3F		
<CR> <LF>			End of message termination

151—GPS Data and Extended Ephemeris Mask

Message ID 151 is used by GSW2 (2.5 or above), SiRFXTrac (2.3 or above), and GSW3 (3.2.0 or above), and GSW3LT software. An example of the message is provided below. Note that the parentheses "(" and ")" are NOT part of the message; they are used to delimit description of a field. The field of checksum consists of two hex digits representing the exclusive or of all characters between, but not including, the \$ and *.

\$PSRF151,(GPS_TIME_VALID_FLAG),(GPS Week),(GPS TOW),
(EPH_REQ_MASK_HEX)*(checksum)<CR><LF>

Table 1-15 contains the parameter definitions and example values.

Table 1-15 GPS Data and Ephemeris Mask - Message 151

Name	Example	Units	Description
Message ID	\$PSRF151		PSRF151 protocol header.
GPS_TIME_VALID_FLAG	0, 1, 2, or 3	N/A	LSB bit 0 = 1, GPS week is valid. LSB bit 0 = 0, GPS week is not valid. LSB bit 1 = 1, GPS TOW is valid. LSB bit 1 = 0, GPS TOW is not valid.
GPS Week	1324	week number	Extended week number (variable length field).
GPS TOW		0.1 second	GPS Time Of Week (variable length field).
EPH_REQ_MASK	0x40000001	N/A	Mask to indicate the satellites for which new ephemeris is needed. Eight characters preceded by the following characters, "0x", are used to show this 32-bit mask (in hex). The leading bit is for satellite PRN 32, and the last bit is for satellite PRN 1.
<CR> <LF>			End of message termination.

152—Extended Ephemeris Integrity

Message ID 152 is used by GSW2 (2.5 or above), SiRFXTrac (2.3 or above), and GSW3 (3.2.0 or above), and GSW3LT software. An example of the message is provided below. Note that the parentheses "(" and ")" are NOT part of the message; they are used to delimit description of a field. The field of checksum consists of two hex digits representing the exclusive or of all characters between, but not including, the \$ and *.

\$PSRF152, (SAT_POS_VALIDITY_FLAG), (SAT_CLK_VALIDITY_FLAG),
(SAT_HEALTH_FLAG)*(checksum) <CR><LF>

Table 1-16 contains the parameter definitions and example values.

Table 1-16 Extended Ephemeris Integrity - Message 152

Name	Example	Units	Description
Message ID	\$PSRF152		PSRF152 protocol header
SAT_POS_VALIDITY_FLAG	0x10000041	N/A	This is a 10 character field representing the debug flag in hex with lead-in "0x". (e.g., 0x00F00000). 1 = invalid position found, 0 = valid position. SVID 1 validity flag is in LSB and subsequent bits will have validity flags for SVIDs in increasing order up to SVID 32 whose validity flag will be in MSB.
SAT_CLK_VALIDITY_FLAG	0x10000041	N/A	This is a 10 character field representing the debug flag in hex with lead-in "0x". (e.g., 0x00F00000). 1 = invalid clock found, 0 = valid clock. SVID 1 validity flag is in LSB and subsequent bits will have validity flags for SVIDs in increasing order up to SVID 32 whose validity flag will be in MSB.
SAT_HEALTH_FLAG	0x10000041	N/A	This is a 10 character field representing the debug flag in hex with lead-in "0x". (e.g., 0x00F00000). 1 = unhealthy satellite, 0 = healthy satellite. SVID 1 health flag is in the LSB and subsequent bits will have health flags for SVIDs in increasing order up to SVID 32 whose validity flag will be in MSB.
<CR> <LF>			End of message termination.

154—Extended Ephemeris ACK

Message ID 154 is used by GSW2 (2.5 or above), SiRFXTrac (2.3 or above), and GSW3 (3.2.0 or above), and GSW3LT software. This message is returned when Messages ID 107, 108, or 110 (input messages) is received. Refer to Chapter 2, "Input Messages" for more details on Messages ID 107, 108, and 110.

An example of the message is provided below. Note that the parentheses "(" and ")" are NOT part of the message; they are used to delimit description of a field. The field of checksum consists of two hex digits representing the exclusive or of all characters between, but not including, the \$ and *.

\$PSRF154, (ACK Message ID)*(checksum) <CR><LF>

Table 1-17 contains the parameter definitions and example values.

Table 1-17 Extended Ephemeris ACK - Message 154

Name	Example	Units	Description
Message ID	\$PSRF154		PSRF154 protocol header.
ACK ID	110	N/A	Message ID of the message to ACK (107, 108, 110).
<CR> <LF>			End of message termination.

Reserved - Message ID 225

This output message is SiRF proprietary except for sub ID 6.

Input Messages



NMEA input messages enable you to control the Evaluation Receiver while in NMEA protocol mode. The Evaluation Receiver may be put into NMEA mode by sending the SiRF binary protocol message “Switch to NMEA Protocol - Message I.D. 129” (see the *SiRF Binary Protocol Reference Manual*). This can be done by using a user program or by using the SiRFS Demo software and selecting Switch to NMEA Protocol from the Action menu (see the *SiRF Evaluation Kit User Guide* or the *SiRFS Demo User Guide*). If the receiver is in SiRF binary mode, all NMEA input messages are ignored. Once the receiver is put into NMEA mode, the following messages may be used to command the module.

Transport Message

Table 2-1 describes the transport message parameters.

Table 2-1 Transport Message Parameters

Start Sequence	Payload	Checksum	End Sequence
\$PSRF<MID> ¹	Data ²	*CKSUM ³	<CR> <LF> ⁴

1. Message Identifier consisting of three numeric characters. Input messages begin at MID 100.
2. Message specific data. Refer to a specific message section for <data>...<data> definition.
3. CKSUM is a two-hex character checksum as defined in the NMEA specification, *NMEA-0183 Standard For Interfacing Marine Electronic Devices*. Use of checksums is required on all input messages.
4. Each message is terminated using Carriage Return (CR) Line Feed (LF) which is \r\n which is hex 0D 0A. Because \r\n are not printable ASCII characters, they are omitted from the example strings, but must be sent to terminate the message and cause the receiver to process that input message.

Note – All fields in all proprietary NMEA messages are required, none are optional. All NMEA messages are comma delimited.

NMEA Input Messages

Table 2-2 describes the NMEA input messages.

Table 2-2 NMEA Input Messages

Message	MID ¹	Description
SetSerialPort	100	Set PORT A parameters and protocol
NavigationInitialization	101	Parameters required for start using X/Y/Z ²
SetDGPSPort	102	Set PORT B parameters for DGPS input
Query/Rate Control	103	Query standard NMEA message and/or set output rate
LLANavigationInitialization	104	Parameters required for start using Lat/Lon/Alt ³
Development Data On/Off	105	Development Data messages On/Off
Select Datum	106	Selection of datum to be used for coordinate transformations
Extended Ephemeris Proprietary 1	107	Extended Ephemeris Proprietary message
Extended Ephemeris Proprietary 2	108	Extended Ephemeris Proprietary message
Extended Ephemeris Debug	110	Extended Ephemeris Debug
Marketing Software Configuration	200	Selection of Marketing Software Configurations
MSK Receiver Interface	MSK	Command message to a MSK radio-beacon receiver

1. Message Identification (MID).

2. Input coordinates must be WGS84.

3. Input coordinates must be WGS84.

Note – NMEA input messages 100 to 106 are SiRF proprietary NMEA messages. The MSK NMEA string is as defined by the NMEA 0183 standard.

Table 2-3 provides a summary of supported SiRF NMEA input messages by the specific SiRF platforms.

Table 2-3 Supported NMEA Input Messages

Message ID	SiRF Software Options				
	GSW2	SiRFDRIve	SiRFXTrac	SiRFLoc	GSW3 GSW3LT
100	Yes	Yes	Yes	Yes	Yes
101	Yes	Yes	Yes ¹	Yes	Yes ¹
102	Yes	Yes	No	No	Yes
103	Yes	Yes	Yes	Yes	Yes
104	Yes	Yes	Yes ¹	Yes	Yes ¹
105	Yes	Yes	Yes	Yes	Yes
106	Yes	Yes	Yes	Yes	Yes
107	2.5 and above	No	2.3 and above	No	Yes
108	2.5 and above	No	2.3 and above	No	Yes
110	2.5 and above	No	2.3 and above	No	3.2.0 and above
200 ²	No	No	No	No	No
MSK	Yes	Yes	No	No	Yes ³

1. Position and time are not available, consequently warm start init is ignored.

2. Only with GSC2xr chip.

3. MSK message for GSW3 and GSW3LT are empty since they do not support BEACON

100—SetSerialPort

This command message is used to set the protocol (SiRF binary or NMEA) and/or the communication parameters (Baud, data bits, stop bits, and parity). Generally, this command is used to switch the module back to SiRF binary protocol mode where a more extensive command message set is available. When a valid message is received, the parameters are stored in battery-backed SRAM and the Evaluation Receiver restarts using the saved parameters.

Table 2-4 contains the input values for the following example:

Switch to SiRF binary protocol at 9600,8,N,1

\$PSRF100,0,9600,8,1,0*0C

Table 2-4 Set Serial Port Data Format

Name	Example	Units	Description
Message ID	\$PSRF100		PSRF100 protocol header
Protocol	0		0=SiRF binary, 1=NMEA
Baud	9600		1200, 2400, 4800, 9600, 19200, 38400, 57600, and 115200
DataBits	8		8,7 ¹
StopBits	1		0,1
Parity	0		0=None, 1=Odd, 2=Even
Checksum	*0C		
<CR> <LF>			End of message termination

1. SiRF protocol is only valid for 8 data bits, 1 stop bit, and no parity.

101—NavigationInitialization

This command is used to initialize the Evaluation Receiver by providing current position (in X, Y, Z coordinates), clock offset, and time. This enables the Evaluation Receiver to search for the correct satellite signals at the correct signal parameters. Correct initialization parameters enable the Evaluation Receiver to acquire signals quickly.

For GSW3, GSW3LT, and SiRFXTrac software, position and time inputs are not possible and consequently warm start init is ignored.

Table 2-5 contains the input values for the following example:

Start using known position and time.

\$PSRF101,-2686700,-4304200,3851624,96000,497260,921,12,3*1C

Table 2-5 Navigation Initialization Data Format

Name	Example	Units	Description
Message ID	\$PSRF101		PSRF101 protocol header
ECEF X	-2686700	meters	X coordinate position
ECEF Y	-4304200	meters	Y coordinate position
ECEF Z	3851624	meters	Z coordinate position
ClkOffset	96000	Hz	Clock Offset of the Evaluation Receiver ¹
TimeOfWeek	497260	seconds	GPS Time Of Week

Table 2-5 Navigation Initialization Data Format (Continued)

Name	Example	Units	Description
WeekNo	921		GPS Week Number
ChannelCount	12		Range 1 to 12
ResetCfg	3		See Table 2-6 and Table 2-7
Checksum	*1C		
<CR> <LF>			End of message termination

1. Use 0 for last saved value if available. If this is unavailable, a default value of 96,000 is used.

Table 2-6 Reset Configuration - Non SiRFLoc Platforms

Hex	Description
0x01	Hot Start— All data valid
0x02	Warm Start—Ephemeris cleared
0x03	Warm Start (with Init)—Ephemeris cleared, initialization data loaded
0x04	Cold Start—Clears all data in memory
0x08	Clear Memory—Clears all data in memory and resets the receiver back to factory defaults

Table 2-7 Reset Configuration - SiRFLoc Specific

Hex	Description
0x00	Perform a hot start using internal RAM data. No initialization data is used.
0x01	Use initialization data and begin in start mode. Uncertainties are 5 seconds time accuracy and 300 km position accuracy. Ephemeris data in SRAM is used.
0x02	No initialization data is used, ephemeris data is cleared, and warm start performed using remaining data in RAM.
0x03	Initialization data is used, ephemeris data is cleared, and warm start performed using remaining data in RAM.
0x04	No initialization data is used. Position, time and ephemeris are cleared and a cold start is performed.
0x08	No initialization data is used. Internal RAM is cleared and a factory reset is performed.

102—SetDGPSPort

This command is used to control the serial port used to receive RTCM differential corrections. Differential receivers may output corrections using different communication parameters. If a DGPS receiver is used that has different communication parameters, use this command to allow the receiver to correctly decode the data. When a valid message is received, the parameters are stored in battery-backed SRAM and the receiver restarts using the saved parameters.

For GSW3 and GSW3LT software, this message does not provide DGPS parameter.

Table 2-8 contains the input values for the following example:

Set DGPS Port to be 9600,8,N,1.

\$PSRF102,9600,8,1,0*12

Table 2-8 Set DGPS Port Data Format

Name	Example	Units	Description
Message ID	\$PSRF102		PSRF102 protocol header
Baud	9600		1200, 2400, 4800, 9600, 19200, 38400, 57600, and 115200
DataBits	8		8,7
StopBits	1		0,1
Parity	0		0=None, 1=Odd, 2=Even
Checksum	*12		
<CR> <LF>			End of message termination

103—Query/Rate Control

This command is used to control the output of standard NMEA messages GGA, GLL, GSA, GSV, RMC, and VTG. Using this command message, standard NMEA messages may be polled once, or setup for periodic output. Checksums may also be enabled or disabled depending on the needs of the receiving program. NMEA message settings are saved in battery-backed memory for each entry when the message is accepted.

Table 2-9 contains the input values for the following examples:

1. Query the GGA message with checksum enabled

\$PSRF103,00,01,00,01*25

2. Enable VTG message for a 1 Hz constant output with checksum enabled

\$PSRF103,05,00,01,01*20

3. Disable VTG message

\$PSRF103,05,00,00,01*21

Table 2-9 Query/Rate Control Data Format (See example 1)

Name	Example	Units	Description
Message ID	\$PSRF103		PSRF103 protocol header
Msg	00		See Table 2-10
Mode	01		0=SetRate, 1=Query
Rate	00	seconds	Output—off=0, max=255
CksumEnable	01		0=Disable Checksum, 1=Enable Checksum
Checksum	*25		
<CR> <LF>			End of message termination

Table 2-10 Messages

Value	Description
0	GGA
1	GLL
2	GSA
3	GSV
4	RMC
5	VTG
6	MSS (If internal beacon is supported)
7	Not defined
8	ZDA (if 1PPS output is supported)
9	Not defined

Note – In TricklePower mode, update rate is specified by the user. When switching to NMEA protocol, the message update rate is also required. The resulting update rate is the product of the TricklePower Update rate and the NMEA update rate (i.e., TricklePower update rate = 2 seconds, NMEA update rate = 5 seconds, resulting update rate is every 10 seconds, (2 X 5 = 10)).

104—LLANavigationInitialization

This command is used to initialize the Evaluation Receiver by providing current position (in latitude, longitude, and altitude coordinates), clock offset, and time. This enables the receiver to search for the correct satellite signals at the correct signal parameters. Correct initialization parameters enable the receiver to acquire signals quickly.

For GSW3, GSW3LT, and SiRFXTTrac software, position and time inputs are not possible and consequently warm start init is ignored.

Table 2-11 contains the input values for the following example:

Start using known position and time.

\$PSRF104,37.3875111,-121.97232,0,96000,237759,1946,12,1*07

Table 2-11 LLA Navigation Initialization Data Format

Name	Example	Units	Description
Message ID	\$PSRF104		PSRF104 protocol header
Lat	37.3875111	degrees	Latitude position (Range 90 to -90)
Lon	-121.97232	degrees	Longitude position (Range 180 to -180)
Alt	0	meters	Altitude position
ClkOffset	96000	Hz	Clock Offset of the Evaluation Receiver ¹
TimeOfWeek	237759	seconds	GPS Time Of Week
WeekNo	1946		Extended GPS Week Number (1024 added)
ChannelCount	12		Range 1 to 12
ResetCfg	1		See Table 2-12
Checksum	*07		

Table 2-11 LLA Navigation Initialization Data Format

Name	Example	Units	Description
<CR> <LF>			End of message termination

1. Use 0 for last saved value if available. If this is unavailable, a default value of 96,000 is used.

Table 2-12 Reset Configuration

Hex	Description
0x01	Hot Start— All data valid
0x02	Warm Start—Ephemeris cleared
0x03	Warm Start (with Init)—Ephemeris cleared, initialization data loaded
0x04	Cold Start—Clears all data in memory
0x08	Clear Memory—Clears all data in memory and resets receiver back to factory defaults

105—Development Data On/Off

Use this command to enable development data information if you are having trouble getting commands accepted. Invalid commands generate debug information that enables the you to determine the source of the command rejection. Common reasons for input command rejection are invalid checksum or parameter out of specified range.

Table 2-13 contains the input values for the following examples:

1. Debug On

\$PSRF105,1*3E

2. Debug Off

\$PSRF105,0*3F

Table 2-13 Development Data On/Off Data Format

Name	Example	Units	Description
Message ID	\$PSRF105		PSRF105 protocol header
Debug	1		0=Off, 1=On
Checksum	*3E		
<CR> <LF>			End of message termination

106—Select Datum

GPS receivers perform initial position and velocity calculations using an earth-centered earth-fixed (ECEF) coordinate system. Results may be converted to an earth model (geoid) defined by the selected datum. The default datum is WGS 84 (World Geodetic System 1984) which provides a worldwide common grid system that may be translated into local coordinate systems or map datums. (Local map datums are a best fit to the local shape of the earth and not valid worldwide.)

Table 2-14 contains the input values for the following examples:

1. Datum select TOKYO_MEAN

\$PSRF106,178*32

Table 2-14 Select Datum Data Format

Name	Example	Units	Description
Message ID	\$PSRF106		PSRF106 protocol header
Datum	178		21=WGS84 178=TOKYO_MEAN 179=TOKYO_JAPAN 180=TOKYO_KOREA 181=TOKYO_OKINAWA
Checksum	*32		
<CR> <LF>			End of message termination

107—Extended Ephemeris Proprietary 1

This message is reserved for SiRF extended ephemeris usage only. The content of this message is proprietary. See also Chapter 1, “Output Messages” Message ID 154.

Table 2-15 contains the message parameter definitions.

Table 2-15 Extended Ephemeris Proprietary 1

Name	Example	Units	Description
Message ID	\$PSRF107		PSRF107 protocol header
Extended Ephemeris			Proprietary message
Checksum			
<CR> <LF>			End of message termination

108—Extended Ephemeris Proprietary 2

This message is reserved for SiRF extended ephemeris usage only. The content of this message is proprietary. See also Chapter 1, “Output Messages” Message ID 154.

Table 2-16 contains the message parameter definitions.

Table 2-16 Extended Ephemeris Proprietary 2

Name	Example	Units	Description
Message ID	\$PSRF108		PSRF108 protocol header
Extended Ephemeris			Proprietary message
Checksum			
<CR> <LF>			End of message termination

110—Extended Ephemeris Debug

This message contains a debug flag. See also Chapter 1, “Output Messages” Message ID 154.

Table 2-17 contains the message parameter definitions.

Table 2-17 Extended Ephemeris Debug

Name	Example	Units	Description
Message ID	\$PSRF110		PSRF110 protocol header.
DEBUG_FLAG	0x01000000		This is a 10 character field representing the debug flag in hex with leading “0x”. If the first byte is set to 0x01 (i.e., Debug_Flag = 0x01000000), the GPS sensor ignores all internal broadcast ephemeris.
Checksum			
<CR> <LF>			End of message termination.

200—Marketing Software Configuration

Note – This message ID 200 is used only with GSC2xr chip.

This input message overrides the Marketing Software Configuration as defined in bits [3:2] of the GSC2xr chip configuration register. The valid input values mapped to the Marketing Software Configuration are described in the next table.

Mapping	
Input Values	Marketing Software Configuration
0	1
1	2
2	3
3	4
4	Standard GSW2 and GSW2x software default configuration ¹

1. The default configuration is SiRF Binary at 38400 bps using UART A and RTCM at 9600 bps using UART B.

Table 2-18 contains the input values for the following example:

Set receiver to Standard GSW2 Default Configuration.

Example:

\$PSRF200,4*3D

Table 2-18 GSC2xr Marketing Software Configuration

Name	Example	Units	Description
Message ID	\$PSRF200		PSRF200 protocol header
Software Configuration Value	4		0=Marketing Software Configuration #1 1=Marketing Software Configuration #2 2=Marketing Software Configuration #3 3=Marketing Software Configuration #4 4=GSW2 and GSW2x Default Configuration
Checksum	*3D		
<CR> <LF>			End of message termination

Table 2-19 GSC2xr Marketing Software Configurations

New Config	Nav Status	Config 4	Config 3	Config 2	Config 1
UARTA		NMEA v2.2	NMEA v2.2	SiRF Binary	NMEA v2.2
UARTB		RTCM	RTCM	NMEA v2.2	SiRF Binary
Build		GSWx2.4.0 and greater	GSWx2.4.0 and greater	GSWx2.4.0 and greater	GSWx2.4.0 and greater, Adaptive Trickle-Power @ 300,1
UARTA Baud		4800 n, 8, 1	19200 n, 8, 1	57600 n, 8, 1	4800 n, 8, 1
UARTB Baud		9600 n, 8, 1	9600 n, 8, 1	115200 n, 8, 1	38400 n, 8, 1
SiRF Binary Output Messages ¹		2, 4, 9, 13, 18, 27, 41, 52	2, 4, 9, 13, 18, 27, 41, 52	2, 4, 9, 13, 18, 27, 41, 52	2, 4, 9, 13, 18, 27, 41, 52
NMEA Messages		RMC, GGA, VTG, GSA (GSV@ 1/5Hz), ZDA	GGA, GLL, GSA, GSV, RMC, VTG, ZDA	GGA, GLL, GSA, GSV, RMC, VTG, ZDA	GGA, GLL, GSA, GSV, RMC, VTG, ZDA
GPIO A (GPIO 1)	No Nav	On	On	On	On
	Nav	100ms on, 1Hz	100ms on, 1Hz	100ms on, 1Hz	100ms on, 1Hz
GPIO B (GPIO 3)	No Nav	Off	Off	Off	Off
	Nav	100ms on, 1Hz	100ms on, 1Hz	100ms on, 1Hz	100ms on, 1Hz
GPIO C (GPIO 13)	No Nav	On	On	On	On
	Nav	1s on, 1s off	1s on, 1s off	1s on, 1s off	1s on, 1s off
GPIO D (GPIO 2)	No Nav	Off	Off	Off	Off
	Nav	On	On	On	On
Static Filter		Off	Off	Off	Off
Track Smoothing		On	On	On	On
WAAS		Disabled	Enabled	Enabled	Disabled
DR		Off	Off	Off	Off

1. SiRF Binary Messages: 2 - Measured Nav Data, 4 - Measured Track Data, 9 - Through Put, 13 - Visible List, 18 - OK to Send, 27 - DGPS Status, 41 - Geodetic Nav Data, 52 - 1 PPS Time Message.

MSK—MSK Receiver Interface

Table 2-20 contains the values for the following example:

\$GPMSK , 318.0,A,100,M,2,*45

Table 2-20 RMC Data Format

Name	Example	Units	Description
Message ID	\$GPMSK		MSK protocol header
Beacon Frequency	318.0	kHz	Frequency to use
Auto/Manual Frequency ¹	A		A : Auto, M : Manual
Beacon Bit Rate	100		Bits per second
Auto/Manual Bit Rate ¹	M		A : Auto, M : Manual
Interval for Sending \$--MSS ²	2	sec	Sending of MSS messages for status

1. If Auto is specified the previous field value is ignored.

2. When status data is not to be transmitted this field is null.

Note – The NMEA messages supported by the Evaluation Receiver does not provide the ability to change the DGPS source. If you need to change the DGPS source to internal beacon, use the SiRF binary protocol and then switch to NMEA.
