

| Core | A_e, cm^2 | A_b, cm^2 | $A_e A_b, \text{cm}^4$ | Output power in watts at | | | | | | | | | Volume, cm^3 |
|------------------------------|--------------------|--------------------|------------------------|--------------------------|--------|--------|--------|--------|---------|---------|---------|---------|-----------------------|
| | | | | 20 kHz | 24 kHz | 48 kHz | 72 kHz | 96 kHz | 150 kHz | 200 kHz | 250 kHz | 300 kHz | |
| EE Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| 814E250 | 0.202 | 0.171 | 0.035 | 1.1 | 1.3 | 2.7 | 4.0 | 5.3 | 8.3 | 11.1 | 13.8 | 16.6 | 0.57 |
| 813E187 | 0.225 | 0.329 | 0.074 | 2.4 | 2.8 | 5.7 | 8.5 | 11.4 | 17.8 | 23.7 | 29.6 | 35.5 | 0.89 |
| 813E343 | 0.412 | 0.359 | 0.148 | 4.7 | 5.7 | 11.4 | 17.0 | 22.7 | 35.5 | 47.3 | 59.2 | 71.0 | 1.64 |
| 812E250 | 0.395 | 0.581 | 0.229 | 7.3 | 8.8 | 17.6 | 26.4 | 35.3 | 55.1 | 73.4 | 91.8 | 110.2 | 1.93 |
| 782E272 | 0.577 | 0.968 | 0.559 | 17.9 | 21.4 | 42.9 | 64.3 | 85.8 | 134.0 | 178.7 | 223.4 | 268.1 | 3.79 |
| E375 | 0.810 | 1.149 | 0.931 | 29.8 | 35.7 | 71.5 | 107.2 | 143.0 | 223.4 | 297.8 | 372.3 | 446.7 | 5.64 |
| E21 | 1.490 | 1.213 | 1.807 | 57.8 | 69.4 | 138.8 | 208.2 | 277.6 | 433.8 | 578.4 | 722.9 | 867.5 | 11.50 |
| 783E608 | 1.810 | 1.781 | 3.224 | 103.2 | 123.8 | 247.6 | 371.4 | 495.1 | 773.7 | 1031.6 | 1289.4 | 1547.3 | 17.80 |
| 783E776 | 2.330 | 1.810 | 4.217 | 135.0 | 161.9 | 323.9 | 485.8 | 647.8 | 1012.2 | 1349.5 | 1686.9 | 2024.3 | 22.90 |
| E625 | 2.340 | 1.370 | 3.206 | 102.6 | 123.1 | 246.2 | 369.3 | 492.4 | 769.4 | 1025.9 | 1282.3 | 1538.8 | 20.80 |
| E55 | 3.530 | 2.800 | 9.884 | 316.3 | 379.5 | 759.1 | 1138.6 | 1518.2 | 2372.2 | 3162.9 | 3953.6 | 4744.3 | 43.50 |
| E75 | 3.380 | 2.160 | 7.301 | 233.6 | 280.4 | 560.7 | 841.1 | 1121.4 | 1752.2 | 2336.3 | 2920.3 | 3504.4 | 36.00 |
| EC Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| EC35 | 0.843 | 0.968 | 0.816 | 26.1 | 31.3 | 62.7 | 94.0 | 125.3 | 195.8 | 261.1 | 326.4 | 391.7 | 6.53 |
| EC41 | 1.210 | 1.350 | 1.634 | 52.3 | 62.7 | 125.5 | 188.2 | 250.9 | 392.0 | 522.7 | 653.4 | 784.1 | 10.80 |
| EC52 | 1.800 | 2.130 | 3.834 | 122.7 | 147.2 | 294.5 | 441.7 | 588.9 | 920.2 | 1226.9 | 1533.6 | 1840.3 | 18.80 |
| EC70 | 2.790 | 4.770 | 13.308 | 425.9 | 511.0 | 1022.1 | 1533.1 | 2044.2 | 3194.0 | 4258.7 | 5323.3 | 6388.0 | 40.10 |

TABLE 7.2a Maximum Available Output Power in Forward Converter Topology

| Core | A_e, cm^2 | A_b, cm^2 | $A_e A_b, \text{cm}^4$ | Output power in watts at | | | | | | | | | Volume, cm^3 |
|-------------------------------|--------------------|--------------------|------------------------|--------------------------|--------|--------|--------|--------|---------|---------|---------|---------|--------------------------|
| | | | | 20 kHz | 24 kHz | 48 kHz | 72 kHz | 96 kHz | 150 kHz | 200 kHz | 250 kHz | 300 kHz | |
| ETD Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| ETD 29 | 0.760 | 0.903 | 0.686 | 22.0 | 26.4 | 52.7 | 79.1 | 105.4 | 164.7 | 219.6 | 274.5 | 329.4 | 5.50 |
| ETD 34 | 0.971 | 1.220 | 1.185 | 37.9 | 45.5 | 91.0 | 136.5 | 182.0 | 284.3 | 379.1 | 473.8 | 568.6 | 7.64 |
| ETD 39 | 1.250 | 1.740 | 2.175 | 69.6 | 83.5 | 167.0 | 250.6 | 334.1 | 522.0 | 696.0 | 870.0 | 1044.0 | 11.50 |
| ETD 44 | 1.740 | 2.130 | 3.706 | 118.6 | 142.3 | 284.6 | 427.0 | 569.3 | 889.5 | 1186.0 | 1482.5 | 1779.0 | 18.00 |
| ETD 49 | 2.110 | 2.710 | 5.718 | 183.0 | 219.6 | 439.2 | 658.7 | 878.3 | 1372.3 | 1829.8 | 2287.2 | 2744.7 | 24.20 |
| Pot Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| 704 | 0.070 | 0.022 | 0.002 | 0.0 | 0.1 | 0.1 | 0.2 | 0.2 | 0.4 | 0.5 | 0.6 | 0.7 | 0.07 |
| 905 | 0.101 | 0.034 | 0.003 | 0.1 | 0.1 | 0.3 | 0.4 | 0.5 | 0.8 | 1.1 | 1.4 | 1.6 | 0.13 |
| 1107 | 0.167 | 0.054 | 0.009 | 0.3 | 0.3 | 0.7 | 1.0 | 1.4 | 2.2 | 2.9 | 3.6 | 4.3 | 0.25 |
| 1408 | 0.251 | 0.097 | 0.024 | 0.8 | 0.9 | 1.9 | 2.8 | 3.7 | 5.8 | 7.8 | 9.7 | 11.7 | 0.50 |
| 1811 | 0.433 | 0.187 | 0.081 | 2.6 | 3.1 | 6.2 | 9.3 | 12.4 | 19.4 | 25.9 | 32.4 | 38.9 | 1.12 |
| 2213 | 0.635 | 0.297 | 0.189 | 6.0 | 7.2 | 14.5 | 21.7 | 29.0 | 45.3 | 60.4 | 75.4 | 90.5 | 2.00 |
| 2616 | 0.948 | 0.407 | 0.386 | 12.3 | 14.8 | 29.6 | 44.4 | 59.3 | 92.6 | 123.5 | 154.3 | 185.2 | 3.53 |
| 3019 | 1.380 | 0.587 | 0.810 | 25.9 | 31.1 | 62.2 | 93.3 | 124.4 | 194.4 | 259.2 | 324.0 | 388.8 | 6.19 |
| 3622 | 2.20 | 0.774 | 1.563 | 50.0 | 60.0 | 120.1 | 180.1 | 240.2 | 375.2 | 500.3 | 625.4 | 750.5 | 10.70 |
| 4229 | 2.660 | 1.400 | 3.724 | 119.2 | 143.0 | 286.0 | 429.0 | 572.0 | 893.8 | 1191.6 | 1489.6 | 1787.5 | 18.20 |

TABLE 7.2a Maximum Available Output Power in Forward Converter Topology (Continued)

| Core | A_e, cm^2 | A_b, cm^2 | $A_e A_b, \text{cm}^4$ | Output power in watts at | | | | | | | | | Volume, cm^3 |
|------------------------------|--------------------|--------------------|------------------------|--------------------------|--------|--------|--------|--------|---------|---------|---------|---------|--------------------------|
| | | | | 20 kHz | 24 kHz | 48 kHz | 72 kHz | 96 kHz | 150 kHz | 200 kHz | 250 kHz | 300 kHz | |
| RM Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| RM5 | 0.250 | 0.095 | 0.024 | 0.8 | 0.9 | 1.8 | 2.7 | 3.6 | 5.7 | 7.6 | 9.5 | 11.4 | 0.45 |
| RM6 | 0.370 | 0.155 | 0.057 | 1.8 | 2.2 | 4.4 | 6.6 | 8.8 | 13.8 | 18.4 | 22.9 | 27.5 | 0.80 |
| RM8 | 0.630 | 0.310 | 0.195 | 6.2 | 7.5 | 15.0 | 22.5 | 30.0 | 46.9 | 62.5 | 78.1 | 93.7 | 1.85 |
| RM10 | 0.970 | 0.426 | 0.413 | 13.2 | 15.9 | 31.7 | 47.6 | 63.5 | 99.2 | 132.2 | 165.3 | 198.3 | 3.47 |
| RM12 | 1.460 | 0.774 | 1.130 | 36.2 | 43.4 | 86.8 | 130.2 | 173.6 | 271.2 | 361.6 | 452.0 | 542.4 | 8.34 |
| RM14 | 1.980 | 1.100 | 2.178 | 69.7 | 83.6 | 167.3 | 250.9 | 334.5 | 522.7 | 697.0 | 871.2 | 1045.4 | 13.19 |
| PQ Cores, Magnetics Inc. | | | | | | | | | | | | | |
| 42016 | 0.620 | 0.256 | 0.159 | 5.1 | 6.1 | 12.2 | 18.3 | 24.4 | 38.1 | 50.8 | 63.5 | 76.2 | 2.31 |
| 42020 | 0.620 | 0.384 | 0.238 | 7.6 | 9.1 | 18.3 | 27.4 | 36.6 | 57.1 | 76.2 | 95.2 | 114.3 | 2.79 |
| 42620 | 1.190 | 0.322 | 0.383 | 12.3 | 14.7 | 29.4 | 44.1 | 58.9 | 92.0 | 122.6 | 153.3 | 183.9 | 5.49 |
| 42625 | 1.180 | 0.502 | 0.592 | 19.0 | 22.7 | 45.5 | 68.2 | 91.0 | 142.2 | 189.6 | 236.9 | 284.3 | 6.53 |
| 43220 | 1.700 | 0.470 | 0.799 | 25.6 | 30.7 | 61.4 | 92.0 | 122.7 | 191.8 | 255.7 | 319.6 | 383.5 | 9.42 |
| 43230 | 1.610 | 0.994 | 1.600 | 51.2 | 61.5 | 122.9 | 184.4 | 245.8 | 384.1 | 512.1 | 640.1 | 768.2 | 11.97 |
| 43535 | 1.960 | 1.590 | 3.116 | 99.7 | 119.7 | 239.3 | 359.0 | 478.7 | 747.9 | 997.2 | 1246.6 | 1495.9 | 17.26 |
| 44040 | 2.010 | 2.490 | 5.005 | 160.2 | 192.2 | 384.4 | 576.6 | 768.8 | 1201.2 | 1601.6 | 2002.0 | 2402.4 | 20.45 |

Note: From Eq. 7.7, $P_o = 0.00050 B_{\max} f A_e A_b / D_{\text{Cma}}$, where P_o is in watts, B_{\max} in gauss, A_e and A_b in square centimeters, f in hertz, D_{Cma} in circular mils per rms ampere, bobbin winding space factor = 40 percent. For $B_{\max} = 1600$ G. For other B_{\max} , multiply by $B_{\max}/1600$. For $D_{\text{Cma}} = 500$ circular mils/rms ampere. For other D_{Cma} , multiply by $500/D_{\text{Cma}}$. For push-pull topology, multiply powers by a factor of 2.

TABLE 7.2a Maximum Available Output Power in Forward Converter Topology (Continued)

| Core | A_e, cm^2 | A_b, cm^2 | $A_e A_b, \text{cm}^4$ | Output power in watts at | | | | | | | | | Volume, cm^3 |
|------------------------------|--------------------|--------------------|------------------------|--------------------------|--------|--------|--------|--------|---------|---------|---------|---------|--------------------------|
| | | | | 20 kHz | 24 kHz | 48 kHz | 72 kHz | 96 kHz | 150 kHz | 200 kHz | 250 kHz | 300 kHz | |
| EE Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| 814E250 | 0.202 | 0.171 | 0.035 | 3.1 | 3.7 | 7.4 | 11.2 | 14.9 | 23.2 | 30.9 | 38.7 | 46.4 | 0.57 |
| 813E187 | 0.225 | 0.329 | 0.074 | 6.6 | 8.0 | 15.9 | 23.9 | 31.8 | 49.7 | 66.3 | 82.9 | 99.5 | 0.89 |
| 813E343 | 0.412 | 0.359 | 0.148 | 13.3 | 16.0 | 31.8 | 47.8 | 63.6 | 99.4 | 132.5 | 165.7 | 198.8 | 1.64 |
| 812E250 | 0.395 | 0.229 | 20.6 | 24.8 | 49.3 | 74.1 | 98.7 | 154.2 | 154.2 | 205.6 | 257.0 | 308.4 | 1.93 |
| 782E272 | 0.577 | 0.968 | 0.559 | 50.0 | 60.3 | 120.1 | 180.4 | 240.2 | 375.3 | 500.4 | 625.6 | 750.7 | 3.79 |
| E375 | 0.810 | 1.149 | 0.931 | 83.4 | 100.5 | 200.1 | 300.6 | 400.2 | 625.4 | 833.9 | 1042.4 | 1250.8 | 5.64 |
| E21 | 1.490 | 1.213 | 1.807 | 161.9 | 195.2 | 388.6 | 583.8 | 777.2 | 1214.6 | 1619.4 | 2024.3 | 2429.1 | 11.50 |
| 783E608 | 1.810 | 1.781 | 3.224 | 288.8 | 348.1 | 693.1 | 1041.2 | 1386.2 | 2166.2 | 2888.4 | 3610.4 | 4332.5 | 17.80 |
| 783E776 | 2.330 | 1.810 | 4.217 | 377.9 | 455.5 | 906.7 | 136.2 | 1813.4 | 2834.0 | 3778.7 | 4723.4 | 5668.1 | 22.90 |
| E625 | 2.340 | 1.370 | 3.206 | 287.2 | 346.2 | 689.2 | 1035.5 | 1378.5 | 2154.3 | 2872.4 | 3590.4 | 4308.6 | 20.80 |
| E55 | 3.530 | 2.800 | 9.884 | 885.6 | 1067.5 | 2125.1 | 3192.5 | 4250.1 | 6642.0 | 8856.1 | 11070.1 | 13284.1 | 43.50 |
| E75 | 3.380 | 2.160 | 7.301 | 654.2 | 788.5 | 1569.7 | 2358.2 | 3139.3 | 4906.1 | 6541.5 | 8176.9 | 9812.3 | 36.00 |
| EC Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| EC35 | 0.843 | 0.968 | 0.816 | 73.1 | 88.1 | 175.4 | 263.6 | 350.9 | 548.4 | 731.2 | 913.9 | 1096.7 | 6.53 |
| EC41 | 1.210 | 1.350 | 1.634 | 146.4 | 176.4 | 351.2 | 527.6 | 702.4 | 1097.7 | 1463.6 | 1829.5 | 2195.4 | 10.80 |
| EC52 | 1.800 | 2.130 | 3.834 | 343.5 | 414.1 | 824.3 | 1238.4 | 1648.6 | 2576.4 | 3435.3 | 4294.1 | 5152.9 | 18.80 |
| EC70 | 2.790 | 4.770 | 13.308 | 1192.4 | 1437.3 | 2861.3 | 4298.6 | 5722.6 | 8943.2 | 11924.2 | 14905.3 | 17886.4 | 40.10 |

TABLE 7.2b Maximum Available Output Power in Half or Full Bridge Topology

| Core | A_e, cm^2 | A_b, cm^2 | $A_e A_b, \text{cm}^4$ | Output power in watts at | | | | | | | | | Volume, cm^3 |
|-------------------------------|--------------------|--------------------|------------------------|--------------------------|--------|--------|--------|--------|---------|---------|---------|---------|-----------------------|
| | | | | 20 kHz | 24 kHz | 48 kHz | 72 kHz | 96 kHz | 150 kHz | 200 kHz | 250 kHz | 300 kHz | |
| ETD Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| ETD 29 | 0.760 | 0.903 | 0.686 | 61.5 | 74.1 | 147.6 | 221.7 | 295.1 | 461.2 | 614.9 | 768.6 | 922.4 | 5.50 |
| ETD 34 | 0.971 | 1.220 | 1.185 | 106.1 | 127.9 | 254.7 | 382.6 | 509.4 | 796.1 | 1061.4 | 1326.8 | 1592.1 | 7.64 |
| ETD 39 | 1.250 | 1.740 | 2.175 | 194.9 | 234.9 | 467.6 | 702.5 | 935.3 | 1461.6 | 1948.8 | 2436.0 | 2923.2 | 11.50 |
| ETD 44 | 1.740 | 2.130 | 3.706 | 332.1 | 400.3 | 796.8 | 1197.1 | 1593.7 | 2490.6 | 3320.8 | 4150.9 | 4981.1 | 18.00 |
| ETD 49 | 2.110 | 2.710 | 5.718 | 512.3 | 617.6 | 1229.4 | 1846.9 | 2458.9 | 3842.6 | 5123.4 | 6404.3 | 7685.1 | 24.20 |
| Pot Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| 704 | 0.070 | 0.022 | 0.002 | 0.1 | 0.2 | 0.3 | 0.5 | 0.7 | 1.0 | 1.4 | 1.7 | 2.1 | 0.07 |
| 905 | 0.101 | 0.034 | 0.003 | 0.3 | 0.4 | 0.7 | 1.1 | 1.5 | 2.3 | 3.1 | 3.8 | 4.6 | 0.13 |
| 704 | 0.070 | 0.022 | 0.002 | 0.1 | 0.2 | 0.3 | 0.5 | 0.7 | 1.0 | 1.4 | 1.7 | 2.1 | 0.07 |
| 905 | 0.101 | 0.034 | 0.003 | 0.3 | 0.4 | 0.7 | 1.1 | 1.5 | 2.3 | 3.1 | 3.8 | 4.6 | 0.13 |
| 1107 | 0.167 | 0.054 | 0.009 | 0.8 | 1.0 | 1.9 | 2.9 | 3.9 | 6.1 | 8.1 | 10.1 | 12.1 | 0.25 |
| 1408 | 0.251 | 0.097 | 0.024 | 2.2 | 2.6 | 5.2 | 7.8 | 10.4 | 16.3 | 21.8 | 27.2 | 32.7 | 0.50 |
| 1811 | 0.433 | 0.187 | 0.081 | 7.3 | 8.7 | 17.4 | 26.2 | 34.8 | 54.4 | 72.6 | 90.7 | 108.8 | 1.12 |
| 2213 | 0.635 | 0.297 | 0.189 | 16.9 | 20.4 | 40.5 | 60.9 | 81.9 | 126.7 | 169.0 | 211.2 | 253.5 | 2.00 |
| 2616 | 0.948 | 0.407 | 0.386 | 34.6 | 41.7 | 83.0 | 124.6 | 165.9 | 259.3 | 345.7 | 432.1 | 518.6 | 3.53 |
| 3019 | 1.380 | 0.587 | 0.810 | 72.6 | 87.5 | 174.2 | 261.6 | 348.3 | 544.4 | 725.8 | 907.2 | 1088.7 | 6.19 |
| 3622 | 2.020 | 0.774 | 1.563 | 140.1 | 168.9 | 336.1 | 505.0 | 672.3 | 1050.7 | 1400.9 | 1751.1 | 2101.3 | 10.70 |
| 4229 | 2.660 | 1.400 | 3.724 | 333.7 | 402.2 | 800.7 | 1202.9 | 1601.3 | 2502.5 | 3336.7 | 4170.9 | 5005.1 | 18.20 |

TABLE 7.2b Maximum Available Output Power in Half or Full Bridge Topology (Continued)

| Core | A_e, cm^2 | A_b, cm^2 | $A_e A_b, \text{cm}^4$ | Output power in watts at | | | | | | | | | Volume, cm^3 |
|------------------------------|--------------------|--------------------|------------------------|--------------------------|--------|--------|--------|--------|---------|---------|---------|---------|--------------------------|
| | | | | 20 kHz | 24 kHz | 48 kHz | 72 kHz | 96 kHz | 150 kHz | 200 kHz | 250 kHz | 300 kHz | |
| RM Cores, Ferroxcube-Philips | | | | | | | | | | | | | |
| RM5 | 0.250 | 0.095 | 0.024 | 2.1 | 2.6 | 5.1 | 7.7 | 10.2 | 16.0 | 21.3 | 26.6 | 31.9 | 0.45 |
| RM6 | 0.370 | 0.155 | 0.057 | 5.1 | 6.2 | 12.3 | 18.5 | 24.7 | 38.5 | 51.4 | 64.2 | 77.1 | 0.80 |
| RM8 | 0.630 | 0.310 | 0.195 | 17.5 | 21.1 | 42.0 | 63.1 | 84.0 | 131.2 | 175.0 | 218.7 | 262.5 | 1.85 |
| RM10 | 0.970 | 0.426 | 0.413 | 37.0 | 44.6 | 88.8 | 133.5 | 177.7 | 277.7 | 370.2 | 462.8 | 555.4 | 3.47 |
| RM12 | 1.460 | 0.774 | 1.130 | 101.3 | 122.0 | 243.0 | 365.0 | 485.9 | 759.4 | 1012.5 | 1265.6 | 1518.8 | 8.34 |
| RM14 | 1.980 | 1.100 | 2.178 | 195.1 | 235.2 | 468.3 | 703.5 | 936.5 | 1463.6 | 1951.5 | 2439.4 | 2927.2 | 13.19 |
| PQ Cores, Magnetics Inc. | | | | | | | | | | | | | |
| 42016 | 0.620 | 0.256 | 0.159 | 14.2 | 17.1 | 34.1 | 51.3 | 68.2 | 106.7 | 142.2 | 177.8 | 213.3 | 2.31 |
| 42020 | 0.620 | 0.384 | 0.238 | 21.3 | 25.7 | 51.2 | 76.9 | 102.4 | 160.0 | 213.3 | 266.6 | 320.0 | 2.79 |
| 42620 | 1.190 | 0.322 | 0.383 | 34.3 | 41.4 | 82.4 | 123.8 | 164.8 | 257.5 | 343.3 | 429.2 | 515.0 | 5.49 |
| 42625 | 1.180 | 0.502 | 0.592 | 53.1 | 64.0 | 127.4 | 191.3 | 254.7 | 398.1 | 530.8 | 663.4 | 796.1 | 6.53 |
| 43.220 | 1.700 | 0.470 | 0.799 | 71.6 | 86.3 | 171.8 | 258.1 | 343.6 | 536.9 | 715.9 | 894.9 | 1073.9 | 9.42 |
| 43230 | 1.610 | 0.994 | 1.600 | 143.4 | 172.8 | 344.1 | 516.9 | 688.1 | 1075.4 | 1433.9 | 1792.4 | 2150.9 | 11.97 |
| 43535 | 1.960 | 1.590 | 3.116 | 279.2 | 336.6 | 670.0 | 1006.6 | 1340.1 | 2094.2 | 2792.3 | 3490.4 | 4188.4 | 17.26 |
| 44040 | 2.010 | 2.490 | 5.005 | 448.4 | 540.5 | 1076.1 | 1616.6 | 2152.1 | 3363.3 | 4484.4 | 5605.5 | 6726.6 | 20.45 |

Note: From Eq. 7.18, $P_o = 0.0014 B_{\max} f A_e A_b / D_{\text{cma}}$, where P_o is in watts, B_{\max} in gauss, A_e and A_b in square centimeters, f in hertz, D_{cma} in circular mils per rms ampere, bobbin winding space factor = 40 percent. For $B_{\max} = 1600$ G. For other B_{\max} , multiply by $B_{\max}/1600$. For $D_{\text{cma}} = 500$ circular mils/rms ampere. For other D_{cma} , multiply by $500/D_{\text{cma}}$.

TABLE 7.2b Maximum Available Output Power in Half or Full Bridge Topology (Continued)