


Mechanical Diagram



Winding Instruction

Primary Winding
Start on pin(s) 2 and wind 36 turns (x 1 filar) of item [5]. in 1 layer(s) from left to right. On the final layer, spread the winding evenly across entire bobbin. Finish this winding on pin(s) 1.
Add 1 layer of tape, item [3], for insulation.

Bias Winding
Start on pin(s) 4 and wind 5 turns (x 2 filar) of item [6]. Wind in same rotational direction as primary winding. Spread the winding evenly across entire bobbin. Finish this winding on pin(s) 3.
Add 3 layers of tape, item [3], for insulation.

Secondary Winding
Start on pin(s) 7 and wind 3 turns (x 4 filar) of item [7]. Spread the winding evenly across entire bobbin. Wind in same rotational direction as primary winding. Finish this winding on pin(s) 6.
Add 2 layers of tape, item [3], for insulation.

Core Assembly
Assemble and secure core halves. Item [1].

Varnish
Dip varnish uniformly in item [4]. Do not vacuum impregnate.

Comments

1. For non margin wound transformers use triple insulated wire for all secondary windings.

Materials

Item	Description
[1]	Core: E25/13/7 (EF25), NC-2H (Nicera) or Equivalent, gapped for ALG of 201 nH/T ²
[2]	Bobbin: Generic, 5 pri. + 5 sec.
[3]	Barrier Tape: Polyester film [1 mil (25 µm) base thickness], 15.30 mm wide
[4]	Varnish
[5]	Magnet Wire: 0.35 mm, Solderable Double Coated
[6]	Magnet Wire: 0.45 mm, Solderable Double Coated
[7]	Triple Insulated Wire: 0.45 mm

Electrical Test Specifications

Parameter	Condition	Spec
Electrical Strength, VAC	60 Hz 1 second, from pins 1,2,3,4 to pins 6,7.	3000
Nominal Primary Inductance, µH	Measured at 1 V pk-pk, typical switching frequency, between pin 1 to pin 2, with all other Windings open.	285
Tolerance, ±%	Tolerance of Primary Inductance	10.0
Maximum Primary Leakage, µH	Measured between Pin 1 to Pin 2, with all other Windings shorted.	8.56

Although the design of the software considered safety guidelines, it is the user's responsibility to ensure that the user's power supply design meets all applicable safety requirements of user's product.

The products and applications illustrated herein (including circuits external to the products and transformer construction) may be covered by one or more U.S. and foreign patents or potentially by pending U.S. and foreign patent applications assigned to Power Integrations. A complete list of Power Integrations' patents may be found at www.power.com.